

CFC, R-502, Mid Point, 60 Hz, 1 - Phase, 115 V

Low Temperature

Production Status: This model is obsolete and is no longer in production for both OEM and service replacement.

Electrical Components

Stator

Resistance:	+-7%	Start Wdg:	3.15	Run Wdg:	0.416
-------------	------	------------	------	----------	-------

External Protector

Part No. 071-0127-30

Usage Description:

Vendor Name

T I

Capacitor

Part No.	014-0008-79	Low MFD:	270.0
----------	-------------	----------	-------

Type:	Start	High MFD:	324.0
-------	-------	-----------	-------

Usage Description:	HIGH TORQUE	Volts:	165
--------------------	-------------	--------	-----

Capacitor

Part No.	014-0008-48	Low MFD:	124.0
----------	-------------	----------	-------

Type:	Start	High MFD:	149.0
-------	-------	-----------	-------

Usage Description:	LOW TORQUE	Volts:	220
--------------------	------------	--------	-----

Current Relays

Part No.	040-0088-04	Usage Description:
----------	-------------	--------------------

T I

Potential Relays

Part No.	040-0001-80	Usage Description:
----------	-------------	--------------------