

CFC, R-12, Mid Point, 60 Hz, 1 - Phase, 230 V
 Medium Temperature

Production Status: This compressor and/or application of this compressor is not available to U.S. OEM customers. A field replacement is currently available through a U.S. Emerson Climate Technologies Wholesaler. Please check with your local Emerson Climate Technologies Representative for international availability.

Electrical Components

| | | | | | |
|---------------|-------|------------|-------|----------|-------|
| Stator | | | | | |
| Resistance: | +/-7% | Start Wdg: | 4.363 | Run Wdg: | 1.703 |

| | | | | | |
|---------------|-------|------------|-----|----------|------|
| Stator | | | | | |
| Resistance: | +/-7% | Start Wdg: | 4.7 | Run Wdg: | 1.68 |

| | | | | |
|---------------------------|-------------|--|--|--|
| External Protector | | | | |
| Part No. | 071-0092-18 | | | |
| Usage Description: | E*A2 ONLY | | | |
| <u>Vendor Name</u> | | | | |
| T I | | | | |

| | | | | |
|---------------------------|-------------|--|--|--|
| External Protector | | | | |
| Part No. | 071-0092-16 | | | |
| Usage Description: | E*A2 OMIT | | | |
| <u>Vendor Name</u> | | | | |
| T I | | | | |

| | | | | |
|--------------------|-------------|-----------|-------|--|
| Capacitor | | | | |
| Part No. | 014-0036-05 | Low MFD: | 108.0 | |
| Type: | Start | High MFD: | 130.0 | |
| Usage Description: | | Volts: | 330 | |

| | | | | |
|--------------------|-------------|-----------|-------|--|
| Capacitor | | | | |
| Part No. | 014-0036-21 | Low MFD: | 108.0 | |
| Type: | Start | High MFD: | 130.0 | |
| Usage Description: | | Volts: | 330 | |

| | | | | |
|--------------------|-------------|-----------|------|--|
| Capacitor | | | | |
| Part No. | 014-0064-10 | Low MFD: | 20.0 | |
| Type: | Run | High MFD: | 0.0 | |
| Usage Description: | | Volts: | 440 | |

| | | | | |
|-------------------------|-------------|--------------------|--|--|
| Potential Relays | | | | |
| Part No. | 040-0166-20 | Usage Description: | | |