

CFC, R-12, Mid Point, 60 Hz, 1 - Phase, 115 V

Low Temperature

Production Status: This compressor and/or application of this compressor is not available to U.S. OEM customers. A field replacement is currently available through a U.S. Emerson Climate Technologies Wholesaler. Please check with your local Emerson Climate Technologies Representative for international availability.

Electrical Components

Stator					
Resistance:	+-7%	Start Wdg:	2.42	Run Wdg:	0.835

External Protector					
Part No.	071-0092-06				
Usage Description:					
<u>Vendor Name</u>	T I				

Capacitor					
Part No.	014-0061-02	Low MFD:	400.0		
Type:	Start	High MFD:	480.0		
Usage Description:		Volts:	110		

Capacitor					
Part No.	014-0058-07	Low MFD:	400.0		
Type:	Start	High MFD:	480.0		
Usage Description:		Volts:	110		

Capacitor					
Part No.	014-0061-05	Low MFD:	430.0		
Type:	Start	High MFD:	516.0		
Usage Description:	SPECIAL APPL. KAG, KAM		Volts:	125	

Capacitor					
Part No.	014-0058-10	Low MFD:	430.0		
Type:	Start	High MFD:	516.0		
Usage Description:		Volts:	125		

Potential Relays					
Part No.	040-0007-00	Usage Description:	SPECIAL, MOUNTED IN TERM. BOX		

Potential Relays					
Part No.	040-0166-08	Usage Description:			