

CFC, R-12, Mid Point, 60 Hz, 1 - Phase, 115 V

Low Temperature

Production Status: This compressor and/or application of this compressor is not available to U.S. OEM customers. A field replacement is currently available through a U.S. Emerson Climate Technologies Wholesaler. Please check with your local Emerson Climate Technologies Representative for international availability.

Electrical Components

Stator

Resistance: +-7% Start Wdg: 2.42 Run Wdg: 0.835

External Protector

Part No. 071-0092-06

Usage Description:

Vendor Name

T I

Capacitor

Part No. 014-0061-02

Type: Start

Usage Description:

Low MFD: 400.0

High MFD: 480.0

Volts: 110

Capacitor

Part No. 014-0058-07

Type: Start

Usage Description:

Low MFD: 400.0

High MFD: 480.0

Volts: 110

Capacitor

Part No. 014-0061-05

Type: Start

Usage Description: SPECIAL APPL. KAG, KAM

Low MFD: 430.0

High MFD: 516.0

Volts: 125

Capacitor

Part No. 014-0058-10

Type: Start

Usage Description:

Low MFD: 430.0

High MFD: 516.0

Volts: 125

Potential Relays

Part No. 040-0007-00

Usage Description: SPECIAL, MOUNTED IN TERM. BOX

Potential Relays

Part No. 040-0166-08

Usage Description: