

HFC, R-134a, Mid Point, 60 Hz, 1 - Phase, 208/230 V

High Temperature

Production Status: Available for sale to all U.S. customers. Please check with your local Emerson Climate Technologies Representative for international availability.**Electrical Components**

| | | | | | |
|---------------|------|------------|-----|----------|------|
| Stator | | | | | |
| Resistance: | +-7% | Start Wdg: | 6.3 | Run Wdg: | 1.65 |

| | | | | | |
|---------------------------|-------------|--|--|--|--|
| External Protector | | | | | |
| Part No. | 071-0127-05 | | | | |
| Usage Description: | | | | | |
| <u>Vendor Name</u> | T I | | | | |

| | | | | | |
|--------------------|-------------|-----------|-------|--|--|
| Capacitor | | | | | |
| Part No. | 014-0061-14 | Low MFD: | 108.0 | | |
| Type: | Start | High MFD: | 130.0 | | |
| Usage Description: | HIGH TORQUE | Volts: | 220 | | |

| | | | | | |
|--------------------|-------------|-----------|------|--|--|
| Capacitor | | | | | |
| Part No. | 014-0064-02 | Low MFD: | 15.0 | | |
| Type: | Run | High MFD: | 0.0 | | |
| Usage Description: | | Volts: | 370 | | |

| | | | | | |
|-------------------------|-------------|--------------------|--|--|--|
| Potential Relays | | | | | |
| Part No. | 040-0166-14 | Usage Description: | | | |

| | | | | | |
|-------------------------|-------------|--------------------|--|--|--|
| Potential Relays | | | | | |
| Part No. | 040-0001-73 | Usage Description: | | | |

| | | | | | |
|-------------------------|-------------|--------------------|--|--|--|
| Potential Relays | | | | | |
| Part No. | 040-0166-32 | Usage Description: | | | |