

HFC, R-134a, Mid Point, 60 Hz, 1 - Phase, 115 V
 Medium Temperature

Production Status: Available for sale to all U.S. customers. Please check with your local Emerson Climate Technologies Representative for international availability.

Electrical Components

Stator			
Resistance:	+/-7%	Start Wdg:	4.07
		Run Wdg:	0.687

External Protector	
Part No.	071-0127-41
Usage Description:	
<u>Vendor Name</u>	
T I	

External Protector	
Part No.	071-0518-02
Usage Description: SPECIAL CUST. APPL.	
<u>Vendor Name</u>	
T I	

Capacitor			
Part No.	014-0061-17	Low MFD:	189.0
Type:	Start	High MFD:	227.0
Usage Description:	HIGH TORQUE	Volts:	220

Capacitor			
Part No.	014-0061-09	Low MFD:	88.0
Type:	Start	High MFD:	106.0
Usage Description:	LOW TORQUE	Volts:	220

Current Relays		
Part No.	040-0168-00	Usage Description:
EMB		

Current Relays		
Part No.	040-0169-00	Usage Description:
EMB		

Potential Relays		
Part No.	040-0001-62	Usage Description:

RS40C2E-IAA



HFC, R-134a, Mid Point, 60 Hz, 1 - Phase, 115 V

Medium Temperature

Production Status: Available for sale to all U.S. customers. Please check with your local Emerson Climate Technologies Representative for international availability.

Electrical Components

Potential Relays

Part No.

040-0166-21

Usage Description: